











The petal 704-petal 718 are coupled to the nadir panel 722 and each to one extension arm 728. The petal 704-petal 718 may be rotatably coupled to each of the nadir panel 722 and the extension arm 728. As the extension plate 726 is moved toward the support structure 702 during the extension phase, force is exerted on each petal via the extension arm 728. The force is then applied to each rotatable joint causing each of the petals to align at a specified angle to the nadir panel 722 once the extension plate 726 has come to rest, e.g. between 5 and 45 degrees. The angle at which each of the petals is maintained contributes to the communication profile of the beams sent and received. As depicted in FIG. 7, the antenna 700 comprises eight (8) petals. In other embodiments, a different number of petals is utilized, such as six (6) petals. In many embodiments, the number of petals is an even number as the petals are grouped as send and receive pairs of petals. A send petal may have neighboring petals that are receive petals (and vice versa) to help ensure that a send petal and a receive petal is oriented toward a ground station. As the number of petals decreases, the antenna 700 is less likely to have an orientation to communicate with a ground station. Increasing the number of petals may increase the size of the antenna 700 (to maintain the same petal size) or decrease the size of each petal. Decreasing the size of each petal may then result in a reduced size of the S-band patches 720, which alters the beam profile for communication. The petal 704-petal 718 each are coupled to one or more S-band patches 720. The S-band patches 720 may be integrated into each of the petals, may be fastened to the petals, etc. As depicted, the antenna 700 has three (3) S-band patches 720 per petal. In some embodiments, each petal may have as few as one (1) patch or as many as eight (8) or more patches. Each of the petals (and patches) may be electrically coupled to a control system of the satellite. When a communication signal is received by a receive petal, the communication signal may be sent to the control system. The control system may then determine the destination of a send signal, select one of the send petals to send the signal, and send the communication signal to the selected send petal to emit the communication signal as part of its beam.

The nadir panel 722 is coupled to the support structure 702 and rotatably coupled to each of the petals. The nadir panel 722 may be coupled to the support structure 702 via intermediary structures (see FIG. 8). The nadir panel 722 may also be coupled to, or contact, an extension mechanism. Such an extension mechanism may also contact or be coupled to the extension plate 726. During the extension phase, the extension mechanism may operate to apply a force to each of the nadir panel 722 and the extension plate 726, causing those components to move away from each other. The nadir panel 722 is coupled to C-band patches 724. The C-band patches 724 may be integrated or fastened to the nadir panel 722. In some embodiments, two (2) C-band patches 724 are coupled to the nadir panel 722. One of the C-band patches 724 may be a send patch, while the other may be a receive patch. Each patch may be wired to a control system of the satellite. During operation, the nadir panel 722 is generally oriented toward the nadir.

The extension plate 726 is rotatably coupled to each extension arm 728. The extension plate 726 may also be slidably coupled to the support structure 702 or intermediary components (see FIG. 8). The extension plate 726 is further coupled or contacted to an extension mechanism. The extension mechanism, when activated, moves the extension plate 726 toward the support structure 702 and away from the nadir panel 722. The extension plate 726 exerts a force on each extension arm 728 via the rotatable coupling.

The extension arm 728 may be rotatably coupled to the extension plate 726 and one of the petals (as depicted, petal 704). In some embodiments, one extension arm 728 is coupled to one petal. In other embodiments, each extension arm 728 may be rotatably coupled to multiple petals. For example the extension arm 728 may be coupled to both petal 704 and the petal 706, resulting in an extension arm 728 with a Y-shape.

Referring to FIG. 8, an antenna 800 comprises a body support structure 802, an extruding mechanism 804, an extrusion plate 806, an extension plate 808, extension arms 810, an extension mechanism 812, an extrusion support structure 814, petals 816, and a nadir panel 818.

The body support structure 802 is coupled to the body of the satellite. The body support structure 802 is also coupled to the extruding mechanism 804. The body support structure 802 may be a hollow housing, such that, when the antenna 800 is in the stowed state, the other components are contained within the body support structure 802. The body support structure 802 may further be slidably coupled to the extrusion plate 806. The body support structure 802 may have a hollow cylindrical portion with an inner diameter that is similar to the







